

# EMERALD-MM-8

8 PORTS, RS-232/422/485 PROTOCOLS, 8 DIGITAL I/O

## SPECIFICATIONS

SERIAL PORTS	
No. of serial ports	8
Protocols	RS-232, RS-422, RS-485 (jumper selected)
Maximum baud rate	460.8kbps
Communications parameters	5, 6, 7, or 8 data bits; Even, odd, or no parity
Short circuit protection	Continuous, all outputs
RS-232 MODE:	
Input impedance	Ω 3Kminimum
Input voltage swing	± 30V maximum
Output voltage swing	± 5V min, ±7V typical
RS-422, RS-485 MODES:	
Differential threshold	-0.2V min, +0.2V max input
Input impedance	Ω12Kminimum
Input current	μ+1.0A max (VIN = 12V) -0.8μA max (VIN = -7V)
Differential output voltage	2.0V min (R= 50Ω)
High/low states differential output voltage symmetry	0.2V maximum
DIGITAL I/O	
No. / Direction	8, individually programmable
Input voltage	Logic 0: -0.3V min, 0.8V max Logic 1: 2.0V min, 5.3V max
Output voltage	Logic 0: 0.0V min, 0.4V max Logic 1: 3.7V min, 5.0V max
Output current	0: 6mA max; 1: -4mA max
GENERAL	
I/O headers	Dual 40-pin headers, 4 ports per
Dimensions	3.55" x 3.775"
Power supply	+5VDC ±10% @ 80mA typical
Operating temp.	-40 to +85°C Extended
Weight	2.6oz / 74g

Emerald-MM-8 has 8 serial ports using two 16C654 UART chips. The 64-byte FIFOs on these UARTS support a higher baud rate of 460.8kbps. The board also features programmable I/O addresses and interrupt levels for maximum flexibility. Configuration data is stored in an on-board EEPROM and is reloaded automatically on power-up.

Emerald-MM-8 is available in a multi-protocol RS-232/422/485 model (EMM-8M-XT) as well as a low-cost fixed RS-232 model (EMM-4232-XT). On EMM-8M-XT, each port's protocol may be selected independently with jumpers.

In RS-232 mode, each port has the full set of 8 signals plus ground. Termination resistors of 120Ω are provided for RS-422/485 protocols and are jumper-selectable.

Interrupt levels may be shared among any or all serial ports and are supported with an on-board status register. 8 digital I/O lines are also included, with independently programmable direction for each line.


The board has two 40-pin I/O headers, with 4 serial ports and 4 DIO lines on each header. Use mating cable C-DB9M-4 (qty. 2). Emerald-MM-8 requires only +5V supply and operates over the industrial temperature range of -40 to +85.

## ORDERING GUIDE

EMM-8M-XT 8 ports configurable RS-232/422/485

EMM-8232-XT 8 ports fixed RS-232

For cables and accessories, see pages 46-47.



- ? Industry-standard design compatible with any popular operating system
- ? 8 asynchronous serial ports
- ? Dual 16C654 UARTs with 64-byte FIFOs
- ? 460.8K max baud rate
- ? RS-232, RS-422, and RS-485 on one board
- ? Low-cost RS-232-only version available
- ? Jumper-selected protocols, independent for each port
- ? Programmable addresses and interrupts
- ? 8 programmable digital I/O lines
- ? Built-in interrupt sharing
- ? +5V-only supply
- ? -40 to +85°C operation

## INPUT/OUTPUT HEADERS (2 PER BOARD)

### RS-232 Configuration

PORT	Signal	Pin	Signal	Pin
PORT 1	DCD 1	1	DSR 1	2
	RXD 1	3	RTS 1	4
	TXD 1	5	CTS 1	6
	DTR 1	7	R11	8
PORT 2	GND	9	DIO A	10
	DCD 2	11	DSR 2	12
	RXD 2	13	RTS 2	14
	TXD 2	15	CTS 2	16
PORT 3	DTR 2	17	R12	18
	GND	19	DIO B	20
	DCD 3	21	DSR 3	22
	RXD 3	23	RTS 3	24
PORT 4	TXD 3	25	CTS 3	26
	DTR 3	27	R13	28
	GND	29	DIO C	30
	DCD 4	31	DSR 4	32
PORT 4	RXD 4	33	RTS 4	34
	TXD 4	35	CTS 4	36
	DTR 4	37	R14	38
	GND	39	DIO D	40

### RS-422 Configuration

PORT	Signal	Pin	Signal	Pin
PORT 1	NC	1	NC	2
	TXD+1	3	TXD-1	4
	GND	5	GND	6
	RXD+1	7	RXD-1	8
PORT 2	GND	9	DIO A	10
	NC	11	NC	12
	TXD+2	13	TXD-2	14
	GND	15	GND	16
PORT 3	RXD+2	17	RXD-2	18
	GND	19	DIO B	20
	NC	21	NC	22
	TXD+3	23	TXD-3	24
PORT 4	GND	25	GND	26
	RXD+3	27	RXD-3	28
	GND	29	DIO C	30
	NC	31	NC	32
PORT 4	TXD+4	33	TXD-4	34
	GND	35	GND	36
	RXD+4	37	RXD-4	38
	GND	39	DIO D	40

### RS-485 Configuration

PORT	Signal	Pin	Signal	Pin
PORT 1	TXD/RXD+1	3	TXD/RXD-1	4
	GND	5	NC	6
	NC	7	NC	8
	GND	9	DIO A	10
PORT 2	NC	11	NC	12
	TXD/RXD+2	13	TXD/RXD-2	14
	GND	15	GND	16
	NC	17	NC	18
PORT 3	GND	19	DIO B	20
	NC	21	NC	22
	TXD/RXD+3	23	TXD/RXD-3	24
	GND	25	GND	26
PORT 4	NC	27	NC	28
	GND	29	DIO C	30
	NC	31	NC	32
	TXD/RXD+4	33	TXD/RXD-4	34
PORT 4	GND	35	GND	36
	NC	37	NC	38
	NC	39	NC	40
	GND	39	DIO D	40

All ports shown in same protocol for simplicity. Each port may be independently configured.

## EMERALD-MM-8 BLOCK DIAGRAM

